



## JEEP JL SPARE TIRE DELETE WIRING GUIDE

---

# LICENSE PLATE LIGHTS

To illuminate the license plate, you'll need to use the lighted LED license bolts to secure the top of your license plate and angle the LED lights downward. The red wire from each light should be connected to the white/blue wire from your OEM tag harness (located in the rear bumper) You will need to extend the 12V wire from the OEM license plate light up into the tailgate. The black wires from the LED license plate lights should be connected to ground.

# 3RD BRAKE LIGHT

To connect the third brake light, you need to connect the white/green wire from your OEM third brake light to the red wire on the new LED strip. The black wire from the LED strip should be connected to the black ground wire from the OEM 3rd brake light harness.

# OPTIONAL CIRCUITS

The following are optional circuits on the LED strip:

- White: Running Light (could be connected to white/blue)
- Yellow: Right Turn (would need to bring in wire from turn signal)
- Green: Left Turn (would need to bring in wire from turn signal)

For questions or concerns, please reach out to us via email at [Go@AmericanAdventureLab.com](mailto:Go@AmericanAdventureLab.com) or by phone at 385.202.4188.